

- Compatible with most LED fixtures
- Industry Standard 0-10 VDC Output
- Programmable with Battery Backup
- Color LCD Touch Screen
- Now with high temp shutdown!



Rollie Systems Programmable Dimmer is a simple to use dimming controller. Born from our commercial series it is fully programmable with start and end times, maximum output power can be set from 0-100% of available power.


Additional features include battery backup for the RTC, a manual mode that can override the timed settings. All user settings are stored in flash memory.



*Main Screen*



*Manual Mode*



*Blank Screen Time*

GENERAL SPECIFICATIONS	
Input Power	12 VDC (Included)
Output power	0 - 10 VDC (1 Amp Max)
Clock	High Accuracy. Battery Backup
Number of Start/Stop Times	1 Each
Dimensions	7.07 x 3.57 x 1.62
Operating Temperature	-40°C to +85°C (-40°F to 185°F)
Number of Loads (Amps)	1Amp or ~ 100 LED Lights